

# Pockels Cell Drivers

## & HV Power Supplies

Range of drivers for Pockels cells are fast HV switches designed to load and unload capacitance of Pockels cell with several nanosecond edges.

Amplitude of output pulses to Pockels cell is about equal to HV supply voltage. Only exception is DP-FAM series drivers that allow to control the amplitude of each pulse by analog voltage input.

Design adaptation for particular OEM customer is possible and can include optimizing of mechanical design, output switch for voltage, repetition rate, rise/fall time and pulse duration lengthening etc.

Almost all the drivers can work in up to 5 MHz bursts. Range of DC/DC type HV power supplies is manufactured to provide a complete Pockels driving solution.



### Main Features

- Low and high repetition rate models covering range from single pulse to 6MHz
- Up to 5MHz in burst
- Square pulse shape
- Controlled by an external trigger pulse
- Fast HV switching for both rise and fall edges
- Wide range of pulse durations
- Low jitter
- For BBO, RTP, KD\*P, CdTe Pockels cells
- Designed for capacitive load

### General Specifications

DRIVER series	PCD-UHR series	PCD-UHRS series
Maximal operating voltage	≤ 9.8 kV	≤ 3.6 kV
Maximal repetition rate	6 MHz	1 MHz
Minimal HV pulse duration	100 ns	15 ns
HV pulse duration extension with no principal limit using pulse regeneration technique	YES	NO
Triggering pulse duration requirement (for two-pulses triggering mode only)	≥ 20 ns	
Triggering pulse amplitude requirement	3.5 – 5 V (50 Ohm input)	
Triggering pulse rise & fall time requirement	≤ 10 ns	≤ 5 ns
Maximal length of leads to Pockels cell	10 cm	
HV pulse delay	25 ns	30 ns
HV pulse jitter	<100 ps	

#### EXTERNAL POWER REQUIREMENTS

HV supply: each model has particular recommendation

Low voltage supply: 24 VDC ±1V

# Product Range

## Driver Selection Table<sup>(1)</sup>

High PRR unipolar output driver.

HV pulse duration  
100-5000ns

**-C** – driver can be made in any configuration - with aluminum housing or open frame  
**-C** – driver in aluminum housing

High PRR Cavity Dumping bipolar output driver.

HV pulse duration  
100-5000ns

High PRR Cavity Dumping driver.  
FULL BRIDGE configuration with output frequency doubling.  
Encased version.

High voltage Cavity Dumping driver.  
HV05Wm HV power supply is included.

High voltage Cavity Dumping driver with HV05Wm HV power supply included.

Encased version.

Fast amplitude modulation driver.

Each pulse can have individual amplitude in full range 0.1 to 2.5kV according to analog input control signal.

Ekspla Electronics p/n	Rep-rate	Voltage	Rise/fall	Power <sup>(2)</sup>
	kHz	kV	< ns	W
<b>PCD-UHR-50-3.6</b>	50	3.6	7	20
<b>PCD-UHR-250-2.6-(C)</b>	250	2.6	6	40
<b>PCD-UHR-250-3.6-(C)</b>	250	3.6	7	75
<b>PCD-UHR-400-1.5-(C)</b>	400	1.5	5.5	20
<b>PCD-UHR-500-2.6-(C)</b>	500	2.6	6.5	90
<b>PCD-UHR-1000-1.8-(C)</b>	1000	1.8	6	80
<b>PCD-UHR-2000-1.5-(C)</b>	2000	1.5	7	120
	kHz	kV	< ns	W
<b>PCD-UHRS-50-3.6</b>	50	3.6	7	20
<b>PCD-UHRS-250-3.6-(C)</b>	250	3.6	7	75
<b>PCD-UHRS-250-2.6-(C)</b>	250	2.6	6	40
<b>PCD-UHRS-500-2.6-(C)</b>	500	2.6	6.5	90
<b>PCD-UHRS-1000-1.8-(C)</b>	1000	1.8	6	80
<b>PCD-UHRS-400-1.5-(C)</b>	400	1.5	5.5	20
	kHz	kV	< ns	W
<b>PCD-UHR-I-250-5.2-C</b>	250	5.2	8.5	100
<b>PCD-UHR-I-300-4.6-C</b>	300	4.6	8	100
<b>PCD-UHR-I-350-4-C</b>	350	4	7.5	100
<b>PCD-UHR-I-1000-3.0-C</b>	1000	3	7.5	100
	kHz	kV	< ns	W
<b>PCD-UHR-II-150-7.0</b>	150	7	9.5	110
<b>PCD-UHR-II-250-7.0-C</b>	250	7	9.5	200
<b>PCD-UHR-II-1000-4.0-C</b>	1000	4	6	230
<b>PCD-UHR-II-1000-3.8-C</b>	1000	3.8	9.5	210
	kHz	kV	< ns	W
<b>PCD-UHR-III-500-7.2-C</b>	500	7.2	8.5	375
<b>PCD-UHR-III-2000-3.4-C</b>	2000	3.4	9.5	360
<b>PCD-UHR-III-2500-3.1-C</b>	2500	3.1	9.5	360
<b>PCD-UHR-III-3000-2.6-C</b>	3000	2.6	8.5	325
	kHz	kV	< ns	W
<b>2PCD-UHR-III-4000-1.7-C</b>	4000	1.7	10.5	360
<b>2PCD-UHR-III-6000-1.3-C</b>	6000	1.3	9	350
<b>2PCD-UHR-500-3.4-C</b>	500	3.4	7	150
<b>2PCD-UHR-1000-2.4-C</b>	1000	2.4	6.5	180
<b>2PCD-UHR-2000-1.6-C</b>	2000	1.6	6	130
	kHz	kV	< ns	W
<b>PCD-UHV-4.2</b>	10	4.2	6	5
<b>PCD-UHV-5.5</b>	5	5.5	7	5
<b>PCD-UHV10-3</b>	8.6	3	10.5/9.5	5
<b>PCD-UHV10-2.5</b>	9.8	2.5	12/10.5	5
	kHz	kV	< ns	W
<b>PCD-UHV-C</b>	10	4.2	6	5
	5	5.5	7	5
	kHz	kV	< ns	W
<b>PCD-UHV10-C</b>	8.6	3	10.5/9.5	5
	9.8	2.5	12/10.5	5
	kHz	kV	< ns	W
<b>DP-FAM-250-2.5</b>	250	2.5	26/13	60
<b>DP-FAM-500-2.5</b>	500	2.5	26/13	120

<sup>1)</sup> All specifications correspond to Pockels cell capacitance 6pF <sup>2)</sup> HV Power consumption, the same heat to be removed by cooling

# Pockels Cell Drivers



PCD-UHR-III,  
2PCD-UHR-III series driver



PCD-UHR, PCD-UHRS  
series open frame OEM driver



PCD-UHR...C, PCD-UHRS...C  
series OEM driver in aluminum housing

## HV Power Supplies

Ekspla Electronics p/n	<b>Output Power</b>	<b>Maximal Voltage – Standard Options</b>	
		<b>W</b>	<b>kV</b>
Encased HV Power Supply  Powering 48V; Voltage range 0 – Umax; Auxiliary output 24V. CAN, RS232, trimmer analog (option) control.	<b>HV-200</b>	200 W	1.8, 2.6, 3.6, 4 kV
	<b>HV-400</b>	400 W	
	<b>HV-2x200</b>	2 x 200 W	±1.5, ±2.0, ±2.6, ±3.6 kV
Encased HV Power Supply  Powering 24V; Voltage range 0.4*Umax – Umax; Trimmer and CAN control.	<b>HV-170</b>	170 W	1.8, 2.6, 3.6 kV
	<b>HV-2x85</b>	2 x 85 W	±1.5, ±1.8 kV
Open frame (PCB) HV Power Supply  Powering 24V; Voltage range 0.4*Umax – Umax; “-CAN” with CAN control, other trimmer control.	<b>HV05Wm</b>	5 W	1.8, 2.8, 4.0, 4.4, 5.0 kV
	<b>HV05Wm-CAN</b>		
	<b>HV40Wm</b>	40 W	1.3, 1.8, 2.5, 3.6, 4.0 kV
	<b>HV40Wm-CAN</b>		
	<b>HV80Wm</b>	80 W	1.8, 2.6, 3.1, 3.6, 4.0 kV
	<b>HV80Wm-CAN</b>		
	<b>HV120Wm</b>	120 W	1.8, 2.6, 3.1, 3.6, kV
	<b>HV120Wm-CAN</b>		
	<b>HV2x60Wm</b>	2 x 60 W	±1.4, ±2.0, ±2.6, ±3.6 kV
	<b>HV2x60Wm-CAN</b>		

Contact Ekspla  
for more details and  
quotation



本社: 〒134-0088 東京都江戸川区西葛西6-18-14 T.I.ビル ☎ 03-3686-4711  
大阪営業所: 〒532-0003 大阪府大阪市淀川区宮原4-1-46 新大阪北ビル ☎ 06-6393-7411  
✉ <https://www.tokyoinst.co.jp> ✉ [sales@tokyoinst.co.jp](mailto:sales@tokyoinst.co.jp)

**TII Group Company** - グローバルにネットワークを広げ、最先端の科学をお客様に提供 -



超高真空・極低温走査型プローブ顕微鏡  
高速分光測定装置、クライオスタット



Nd:YAGレーザー、Ti:Sレーザー  
OPOレーザー



Enviro ESCA (準大気圧XPS)  
ARPESなど